

Flaglite



The Flaglite Emergency Exit luminaire ensures that the Australian and New Zealand safety standards are met. It combines functionality and good looks in this one visually pleasing package

This Flaglite unique design guarantees that it provides excellent light distribution whilst also producing maximum illuminance in an emergency.

The light is evenly spread across the diffuser creating a highly visible EXIT sign.

The Flaglite is discretely recessed into the buildings false ceiling and it provides clear widespread illumination.

One of its many features is that the one Flaglite Exit fitting can adapt to a multitude of variations.

The Flaglite body comes complete with a three-core flexible cable and a three-pin plug top.

It is easy to install, simply cut out the ceiling panel to cater for the Flaglite body, plug the Flaglite into the loom wiring plug base and tighten the screw on the spring toggles provided.

Flaglite Features

- 10 watt T8 Fluorescent tube
- New charging technology for low power consumption and longer battery life.
- The Flaglite's attractive design compliments and enhances the luminaires capabilities by providing excellent light distribution.
- It comes complete with a 1.5 metre flex and plug.
- The Flaglite is compatible with the Sentinel Self-Testing and the BardicNet-Computer Monitoring Systems.
- High temperature batteries are used to ensure maximum illuminance and longevity in times of an emergency
- A black version is available for theatres and auditoriums
- It is Electro Magnetic Compatible (EMC) compliant
- 12 month warranty
- Complies with Australian & New Zealand Standards AS/NZ 2293.1 1998

AUSTRALIA

Head Office

9 Mosrael Place
Rowville Victoria 3178
Telephone: (61 3) 9763 0555
Facsimile: 1300 733 005

New South Wales

Unit 21/14 Stanton Road
Seven Hills NSW 2147
Telephone: (61 2) 9674 3187
Facsimile: 1300 733 005

Queensland

Comsec Business Park
433 Logan Street
Stones Corner QLD 4120
Telephone: (61 7) 3394 8249
Facsimile: 1300 733 005

South Australia

89A Grange Road
Allenby Gardens SA 5009
Telephone: (61 8) 8340 4081
Facsimile: 1300 733 005

Western Australia

PO Box 837
Scarborough WA 6922
Telephone: (61 8) 9245 1121
Facsimile: 1300 733 005

B-Type Agencies Pty Ltd

Unit 2/15 Narloo Street
Malaga 6090 Perth
Western Australia
Telephone: 08 9209 2220
Facsimile: 08 9209 2229
Infor@btype.com.au

NEW ZEALAND

Auckland

Unit B 237 Bush Road
Albany, Auckland
Telephone: (649) 415 6615
Facsimile: (649) 415 8160

Wellington

Unit 7 30-32 Downer Street
Lower Hutt, Wellington
Telephone: (644) 586 6188
Facsimile: (644) 586 6088

Christchurch

8 Kirkdale Place
Avonhead, Christchurch
Telephone: (643) 358 8444
Facsimile: (643) 358 8446

Function:

Maintained
10 watt

Battery:

High Temperature
Nickel Cadmium
Nickel Metal Hydrate

Emergency duration:

Two Hours or better

Body Construction:

Metal

Diffuser:

Acrylic

Charger:

Dual rate

Sentinel Compatible:

Yes

